

AC TEST SET - 350kV



High Voltage Test and Measuring Equipment (AC Test Set) 350kV, 350kVA

Consisting of :

SL. No.	DESCRIPTION	TYPE	QTY.
1.	HV Test Transformer Pri. 600V, 50Hz Sec. 300 kV, 75 kVA continuous 350 kVA short time Partial Discharge < 10 pC upto rated voltage (350 kV)	TEO350/350Z	1
2.	Control Desk (Motorised) With Oil cooled Auto transformer, Switching cabinet	SRP0.5/50E	1
3.	Capacitor (Measuring) 350 kV, 100pF PD < 5 pC	CM350	1
4.	Voltmeter (AC peak--- 4.5 Digit, Digital Display)	DSM	1
5.	Electrodes for Corona free operation of HV Transformer	EL350	1
6.	Compensating Reactor	DEL300-T	1

Pre-despatch Tests at our Works on No-Load :

HV Transformer Type **TEO350/350Z**

- a) No-Load and short circuit Tests
- b) HV withstand Test at: 385kV 50 Hz, for 1 minute
- c) 5 flashover Tests at 350 kV
- c) Partial Discharge Test before and after the Test (b) & (c) at 20 % Voltage Intervals.

Capacitor (Measuring) Type **CM350**

- a) HV withstand Test at 385kV, 50 Hz, for 1 minute.
- b) Measurement of capacitance and $\tan \delta$ at 20% Voltage Intervals.
- c) Measurement of Partial Discharge at 20% voltage Intervals.



W.S. TEST SYSTEMS PRIVATE LIMITED

27th KM, Bellary Road, Doddajala Post, BANGALORE - 562157, INDIA. Email: marketing@wstestsystems.com